


Manufacturer WAC Lighting
Model BA-LED4
Description LED Bar Light for Undercabinet
Driver Integral
Nominal Power (W) 4.8
Dimming Control Forward- and Reverse-phase
Product Range BA-LED2, BA-LED4, BA-LED6, BA-LED8, BA-LED10
Test Date 3/13/2013

Dimmer Tested Against:	SDM12-EM	EDIMMOD	DRD4
Pass/Fail	Pass	Pass	Pass
Best-Fit Power Profile:			Fail
Minimum ON	6	3	
Maximum ON	78	70	
Adjust	60	100	
Light Output Range (vs. non-dimmed)			
Maximum (Perceived)	96.8%	97.9%	100.0%
Minimum (Perceived)	9.3%	15.9%	8.4%
Minimum (Measured)	0.9%	2.5%	0.7%

Dimmer Equivalent Power (W) 20 24

Linearity Curves (Best-fit Power Profile Applied):



Observations:

Level stepping on long fade.


Minimum Reliable On for DRD4 is 9%.

Forward-phase

100% Dim Level Waveform Capture



50% Dim Level Waveform Capture



Reverse-phase

100% Dim Level Waveform Capture

